# TRIDONIC

**LED Driver** Compact dimming

# IP20 SELV 🖲 🖤 [III @ 💩 C E 🔣 Rohs]

# Driver LCAI 35W 350mA-900mA ECO C

ECO series

# Product description

- Dimmable built-in LED Driver for LED
- Constant current LED Driver
- Output current adjustable between 350 900 mA
- Max. output power 35 W
- Nominal life-time up to 100,000 h
- 5-year guarantee
- Dimming range 1 ... 100 %

#### Properties

- Casing: polycarbonate, white
- Type of protection IP20

# Interfaces

- DALI DEVICE Type 6
- DSI
- switchDIM (with memory function)
- corridorFUNCTION
- Input for temperature sensor (LED temperature monitoring)

# Functions

- Adjustable output current (I-select resistor or DALI)
- Power-up fading at AC
- Intelligent Temperature Guard (overtemperature protection)
- Short-circuit proof
- Overload protection
- Constant Light Output function
- Suitable for emergency escape lighting systems acc. to EN50172

#### $\rightarrow$

# Standards, page 5



Туре	Article	Packaging	Packaging	Weight per pc.	
	number	carton	pallet		
LCAI 35W 350mA-900mA ECO C	28000124	10 pc(s).	960 pc(s).	0.171 kg	

# Technical data

Rated supply voltage	220 – 240 V
AC voltage range	198 – 264 V
DC voltage range	176 – 280 V
Mains frequency	0 / 50 / 60 Hz
Overvoltage protection	320 V AC, 48 h
Typ. current (at 230 V, 50 Hz, full load) <sup>® @</sup>	130 – 185 mA
Typ. current (220 V, 0 Hz, full load, 15 % dimming level)®	32 – 36 mA
Leakage current (PE)	< 0.35 mA
Max. input power	41 W
Typ. efficiency (at 230 V / 50 Hz / full load)®	87 – 90 %
λ (at 230 V, 50 Hz, full load) <sup>®</sup>	≥ 0.98
Typ. power input on stand-by®	70 – 100 mW
THD (at 230 V, 50 Hz, full load)	< 5 %
Time to light (at 230 V, 50 Hz, full load, acc. to DALI)	< 0.6 s
Time to light (DC mode )	< 0.2 s
Switchover time (AC/DC)	< 0.2 s
Turn off time (at 230 V, 50 Hz, full load)	< 20 ms
Hold on time (at 230 V, 50 Hz, full load)⊕	< 14 ms
Output current tolerance® ®	± 3 %
Output LF current ripple (< 120 Hz)	< 2 %
Max. peak output current	≤ output current + 18 %
PWM frequency®	500 Hz
Dimming range	1 – 100 %
Max. output voltage	120 V
Burst / surge peaks output side against PE	1.2 kV
Dimensions L x W x H	120 x 70 x 28.3 mm

# Specific technical data

Туре	Output	Min. forward	Max. forward	Max. outpu	t Typ. power consumptio (at 230 V. 50 Hz. full loa	n Typ. current consumption d) (at 230 V 50 Hz, full load)	Max. casing temperature to	Ambient	I-select resistor value
	350 mA	40 V	900 V	315 W	350.W	152 mA	80 °C	-25 +60 °C	open
	375 mA	40 V	200 V	31.5 W	376 W	163 mA	80 °C	=25 +60 °C	7150 k0
	400 mA	30 \/	88.0 V	35.0 W	37.0 W	165 mA	80 °C	=25 +60 °C	66.50 k0
	425 mA	37 V	82.5 V	35.0 W	38.2 W	167 mA	80 °C	-25 +60 °C	6190 k0
	450 mA	35 V	78.0 V	35.0 W	38.6 W	169 mA	80 °C	-25 +60 °C	5760 k0
	475 mA	33 V	74.0 V	35.0 W	38.9 W	170 mA	80 °C	-25 +60 °C	53.60 kΩ
	500 mA	31 V	70.5 V	35.0 W	39.2 W	172 mA	80 °C	-25 +60 °C	49.90 kΩ
	525 mA	30 V	67.0 V	35.0 W	39.3 W	173 mA	80 °C	-25 +60 °C	45.30 kΩ
	550 mA	28 V	64.0 V	35.0 W	39.4 W	173 mA	80 °C	-25 +60 °C	42.20 kΩ
	575 mA	27 V	61.0 V	35.0 W	39.4 W	174 mA	80 °C	-25 +60 °C	38.30 kΩ
	600 mA	26 V	58.5 V	35.0 W	39.5 W	175 mA	80 °C	-25 +60 °C	35.70 kΩ
LCAI 35W 350mA-900mA ECO C	625 mA	25 V	56.5 V	35.0 W	39.6 W	175 mA	80 °C	-25 +60 °C	32.40 kΩ
	650 mA	24 V	54.0 V	35.0 W	39.7 W	176 mA	80 °C	-25 +60 °C	28.70 kΩ
	675 mA	23 V	52.0 V	35.0 W	39.7 W	176 mA	80 °C	-25 +60 °C	26.10 kΩ
	700 mA	22 V	50.5 V	35.0 W	39.8 W	177 mA	80 °C	-25 +60 °C	22.00 kΩ
	725 mA	21 V	48.5 V	35.0 W	39.9 W	178 mA	80 °C	-25 +60 °C	17.40 kΩ
	750 mA	21 V	47.0 V	35.0 W	40.0 W	179 mA	80 °C	-25 +60 °C	15.00 kΩ
	775 mA	20 V	45.5 V	35.0 W	40.1 W	180 mA	80 °C	-25 +60 °C	12.40 kΩ
	800 mA	19 V	44.0 V	35.0 W	40.3 W	181 mA	80 °C	-25 +60 °C	10.00 kΩ
	825 mA	19 V	42.5 V	35.0 W	40.4 W	182 mA	80 °C	-25 +60 °C	7.68 kΩ
	850 mA	18 V	41.5 V	35.0 W	40.5 W	183 mA	80 °C	-25 +60 °C	5.36 kΩ
	875 mA	17 V	40.5 V	35.0 W	40.6 W	184 mA	80 °C	-25 +60 °C	3.16 kΩ
	900 mA	17 V	39.0 V	35.0 W	40.7 W	185 mA	80 °C	-25 +60 °C	short circuit (0 $\Omega$ )

<sup>®</sup> Valid at 100 % dimming level.

<sup>©</sup> Depending on the selected output current.

<sup>®</sup> Depending on the DALI traffic at the interface.

<sup>④</sup> At power failure.

<sup>⑤</sup> ± 20 %.

<sup>®</sup> At full load.

 $\ensuremath{^{\textcircled{0}}}$  Output current is mean value.

ACCES-SORIES

**I-SELECT PLUG TOP / ECO** 

# Product description

- Ready-for-use resistor to set output current value
- Compatible with LED Driver series TOP and ECO
- Resistor is base isolated
- Resistor power 0.25 W
- Resistor value tolerance ± 1 %



# Ordering data

Туре	Article number	Colour	Marking	Resistor value	Packaging bag	Weight per pc.
I-SELECT PLUG 400mA GN	28000451	Green	0400	66.50 kΩ	10 pc(s).	0.001 kg
I-SELECT PLUG 450mA GN	28000452	Green	0450	57.60 kΩ	10 pc(s).	0.001 kg
I-SELECT PLUG 500mA GN	28000277	Green	0500	49.90 kΩ	10 pc(s).	0.001 kg
I-SELECT PLUG 550mA GN	28000453	Green	0550	42.20 kΩ	10 pc(s).	0.001 kg
I-SELECT PLUG 600mA GN	28000454	Green	0600	35.70 kΩ	10 pc(s).	0.001 kg
I-SELECT PLUG 650mA GN	28000455	Green	0650	28.70 kΩ	10 pc(s).	0.001 kg
I-SELECT PLUG 700mA GN	28000278	Green	0700	22.00 kΩ	10 pc(s).	0.001 kg
I-SELECT PLUG 750mA GN	28000456	Green	0750	15.00 kΩ	10 pc(s).	0.001 kg
I-SELECT PLUG 800mA GN	28000457	Green	0800	10.00 kΩ	10 pc(s).	0.001 kg
I-SELECT PLUG 850mA GN	28000458	Green	0850	5.36 kΩ	10 pc(s).	0.001 kg
I-SELECT PLUG MAX GR	28000274	Grey	MAX	0 Ω	10 pc(s).	0.001 kg

ACCES-SORIES

# LCF 12V FAN DRIVER

# **Product description**

- Fan driver module with 12.4 V output voltage
- Drives the fan permanently (independent of the optional temperature sensor)
- Terminal IN1 / IN2: stranded wires 0.2 mm², stripped wire endings twisted and tin-plated
- Terminal FAN+ / FAN- and OUT1 / OUT2: 0.2 0.75 mm<sup>2</sup> solid or stranded wires twisted and tin-plated, strip wires 6 – 7 mm
- Max. output power of the LED Driver will be reduced by the power consumption of the fan and LCF 12V FAN DRIVER

Technical d	lata
-------------	------

Input voltage, DC	25 – 120 V
Output voltage DC	12.4 V
Max. output current (input voltage 25 – 49 V)	50 mA
Max. output current (input voltage 50 – 120 V)	70 mA
Max. power consumption incl. fan (at 30 mA)	0.55 W
Max. power consumption incl. fan (at 50 mA)	0.90 W
Max. power consumption incl. fan (at 70 mA)	1.25 W
tc point	75 ℃
Ambient temperature ta (at life-time 50,000 h)	-25 +65 ℃
Dimensions LxWxH	45 x 23 x 14 mm



# Ordering data

Гуре	Article number	Packaging carton	Packaging pallet	Weight per pc.
CF 12V FAN DRIVER	28000932	50 pc(s).	1,200 pc(s).	0.01 kg

# Standards

EN 55015 EN 61000-3-2 EN 61000-3-3 EN 61347-1 EN 61347-2-13 EN 62384 EN 61547 EN 62386-101 (according to DALI standard V1) EN 62386-102 EN 62386-207 According to EN 50172 for use in central battery systems According to EN 60598-2-22 suitable for emergency lighting installations

Housing fulfils requirements for reinforced insulation according EN 60598-1.

#### **Overload protection**

If the output voltage range is exceeded the LED Driver turns off the LED output. After restart of the LED Driver the output will be activated again. The restart can either be done via mains reset or via interface (DALI, DSI, switchDIM).

#### **Overtemperature protection**

The LED Driver is protected against temporary thermal overheating. If the temperature limit is exceeded the output current of the LED is reduced. The temperature protection is activated approx. +5 °C above tc max (see page 2). On DC operation this function is deactivated to fulfill emergency requirements.

#### Short-circuit behaviour

In case of a short circuit at the LED output the LED output is switched off. After restart of the LED Driver the output will be activated again. The restart can either be done via mains reset or via interface (DALI, DSI, switchDIM).

#### **No-load operation**

The LED Driver will not be damaged in the no-load operation. The output will be deactivated and therefore free of voltage. If a LED load is connected the device has to be restarted before the output will be activated again.

#### Hot plug-in

Hot plug-in is not recommend within 5 s after shutdown due to output voltage of > 0 V. If a LED load is connected the device has to be restarted before the output will be activated again.

This can be done with mains reset, DALI, DSI or switchDIM.

#### Conditions of use and storage

Humidity:

5 % up to max. 85 %, not condensed (max. 56 days/year at 85 %)

Storage temperature:

The devices have to be within the specified temperature range (ta) before they can be operated.

-40 °C up to max. +80 °C

#### Glow wire test

according to EN 61347-1 with increased temperature of 850 °C passed.

#### Expected life-time

Туре	Output current	ta	40 °C	50 °C	55 °C	60 °C
LCAI 35W 350mA-900mA	750 000 mA	tc	70 ℃	75 °C	80 °C	80 °C
ECO C	550 - 900 IIIA	Life-time	> 100,000 h	100,000 h	75,000 h	50,000 h

The LED Driver is designed for a life-time stated above under reference conditions and with a failure probability of less than 10 %.

#### Maximum loading of automatic circuit breakers

Automatic circuit breaker type	C10	C13	C16	C20	B10	B13	B16	B20	Inrush	current
Installation Ø	1.5 mm <sup>2</sup>	1.5 mm <sup>2</sup>	2.5 mm <sup>2</sup>	4 mm <sup>2</sup>	1.5 mm <sup>2</sup>	1.5 mm <sup>2</sup>	2.5 mm <sup>2</sup>	4 mm <sup>2</sup>	l max	time
LCAI 35W 350mA-900mA ECO C	26	36	42	50	13	18	21	25	5 A	20 µs

#### Harmonic distortion in the mains supply (at 230 V / 50 Hz and full load) in %

	THD	3.	5.	7.	9.	11.
LCAI 35W 350mA-900mA ECO C	< 5	5	1	1	1	1

# Control input (DA/N, DA/L)

Digital DALI signal or switchDIM can be wired on the same terminals (DA/N and DA/L).

### Digital signal DALI/DSI

The control input is non-polar for digital control signals (DALI, DSI). The control signal is not SELV. Control cable has to be installed in accordance to the requirements of low voltage installations. Different functions depending on each module.

#### switchDIM

Integrated switchDIM function allows a direct connection of a push to make switch for dimming and switching.

Brief push (< 0.6 s) switches LED Driver ON and OFF. The LED Drivers switch-ON at light level set at switch-OFF.

When the push to make switch is held, LED modules are dimmed. After repush the LED modules are dimmed in the opposite direction. In installations with LED Drivers with different dimming levels or opposite dimming directions (e.g. after a system extension), all LED Drivers can be synchronized to 50 % dimming level by a 10 s push.

Use of push to make switch with indicator lamp is not permitted.

#### corridorFUNCTION

The corridorFUNCTION can be programmed in two different ways. To program the corridorFUNCTION by means of software a DALI-USB interface is needed in combination with a DALI PS. The software can be the masterCONFIGURATOR.

To activate the corridorFUNCTION without using software a voltage of 230 V simply has to be applied for five minutes at the switchDIM connection. The unit will then switch automatically to the corridorFUNCTION.

#### Note:

If the corridorFUNCTION is wrongly activated in a switchDIM system (for example a switch is used instead of pushbutton), there is the option of installing a pushbutton and deactivating the corridorFUNCTION mode by five short pushes of the button within three seconds.

switchDIM and corridorFUNCTION are very simple tools for controlling ballasts with conventional momentary-action switches or motion sensors. To ensure correct operation a sinusoidal mains voltage with a frequency of 50 Hz or 60 Hz is required at the control input.

Special attention must be paid to achieving clear zero crossings. Serious mains faults may impair the operation of switchDIM and corridorFUNCTION.

# Dimming

Dimming range 1 % to 100 % Digital control with:

- DSI signal: 8 bit Manchester Code Speed 1% to 100 % in 1.4 s
- DALI signal: 16 bit Manchester Code Speed 1% to 100% in 0.2 s Programmable parameter: Minimum dimming level Maximum dimming level Default minimum = 1% Programmable range 1%  $\leq$  MIN  $\leq$  100% Default maximum = 100% Programmable range 100%  $\geq$  MAX  $\geq$  1%

Dimming curve is adapted to the eye sensitiveness.

Dimming is realized by a combination of analog amplitude dimming and PWM dimming.

35 ... 100 %: amplitude dimming 1 ... 34 %: PWM dimming

### **Dimming characteristics**

Digital dimming value



Dimming characteristics as seen by the human eye

#### DC emergency operation

The LED Driver is designed for operation on DC voltage and pulsed DC voltage.

Light output level in DC operation: programmable 1 – 100 % (EOFx = 0.13). Programming by extended DSI or DALI signal (16 bit). Default value is 15 % In DC operation dimming mode can be activated.

The voltage-dependent input current of Driver incl. LED module is depending on the used load.

The voltage-dependent no-load current of Driver (without or defect LED module) is for: AC: 20.5 mA DC: 5.5 mA

#### Function: adjustable current (I-select)

The output current of the LED Driver can be selected between 350 and 900 mA. For adjustment there are two options available.

#### Option 1: "I-select resistor"

In 25 mA steps adjustable (see page 2, specific technical data, "I-select resistor value").

Relationship between output current and resistor value can be found at the table "Specific technical data". Resistor values specified from standardised resistor value ranges. Resistor value tolerance has to be  $\leq 1$  %. Resistor power has to be  $\geq 0.1$  W.

If the resistor is connected with wires a max. wire length of 2 m may not be exceeded and possible interferences have to be avoided.

Resistors for the main output current values can be ordered from Tridonic (see accessories).

# Option 2: DALI

Adjustment is done by masterCONFIGURATOR (see masterCONFIGURATOR documentation).

# Constant light output (CLO)

The luminous flux of an LED decreases constantly over the life-time. The CLO function ensures that the emitted luminous flux remains stable. For that purpose the LED current will increas continously over the LED life-time. In masterCONFIGURATOR it is possible to select a start value (in percent) and an expected life-time. The LED Driver adjusts the current afterwards automatically.

#### Intelligent temperature monitoring (ITM)

The device offers the possibility to connect a silicium based temperature sensor (KTY81-210, KTY82-210) to monitor the LED temperature and protect the module against thermal damages.

If the temperature limit is exceeded the LED output will be dimmed or turned off. If the temperature falls below threshold the device will automatically return to the nominal operation.

The use of a NTC or PTC resistor is not possible.

The device can be operated without a sensor (default setting). The function can be adjusted via masterCONFIGURATOR.

#### Power-up fading

The power-up fading function offers the opportunity to realise a soft start. The soft start will be applied at turning on the mains and at starts by switchDIM.

The function is programmed as a DALI fade time in the range from 0.7 to 16 seconds and dimms in the selected time from 0 % to the power-on level. By factory default power-up fading is not active (0 seconds).

#### Programming

With appropriate software and a USB interface different functions can be activated and various parameters can be configured in the LED Driver. All that is needed is a DALI-USB and the software (masterCONFIGURATOR).

# masterCONFIGURATOR

### At version 2.8:

For programming functions (CLO, I-SET, ITM, power-up fading, corridorFUNCTION) and device settings (fade time, ePowerOnLevel, DC level, etc.). For further information see masterCONFIGURATOR manual.

# **LED Driver** Compact dimming

#### Installation instructions

Wiring type and cross section

The wiring can be in stranded wires with ferrules or solid with a cross section of 0.5–1.5 mm<sup>2</sup> for mains wires and 0.2–1.5 mm<sup>2</sup> for secondary wires. Strip 9.5 mm of insulation from the cables to ensure perfect operation of the push-wire terminals.

Use one wire for each terminal connector only.

# wire preparation:



#### Release of the wiring

Press down the "push button" and remove the cable from front.



#### Wiring guidelines

- The cables should be run separately from the mains connections and mains cables to ensure good EMC conditions.
- The LED wiring should be kept as short as possible to ensure good EMC. The max. secondary cable length is 2 m (4 m circuit), this applies for LED output as well as for I-SET and temperature sensor.
- · Secondary switching is not permitted.
- The LED Driver has no inverse-polarity protection on the secondary side.
  Wrong polarity can damage LED modules with no inverse-polarity protection.

#### Earth connection

The earth connection is conducted as protection earth (PE). If the LED Driver will be earthed, protection earth (PE) has to be used. There is no earth connection required for the functionality of the LED Driver. Earth connection is recommended to improve following behaviour.

- Electromagnetic interferences (EMI)
- LED glowing at stand-by
- Transmission of mains transients to the LED output

In general it is recommended to earth the LED Driver if the LED module is mounted on earthed luminaire parts respectively heat sinks and thereby representing a high capacity against earth.

#### Installation note

Max. torque at the clamping screw: 0.5 Nm / M4

#### Isolation and electric strength testing of luminaires

Electronic devices can be damaged by high voltage. This has to be considered during the routine testing of the luminaires in production.

According to IEC 60598-1 Annex Q (informative only!) or ENEC 303-Annex A, each luminaire should be submitted to an isolation test with 500 V  $_{\rm DC}$  for 1 second. This test voltage should be connected between the interconnected phase and neutral terminals and the earth terminal. The isolation resistance must be at least 2 M $\Omega$ .

As an alternative, IEC 60598-1 Annex Q describes a test of the electrical strength with 1500 V  $_{AC}$  (or 1.414 x 1500 V  $_{DC}$ ). To avoid damage to the electronic devices this test must not be conducted.

# Circuit diagram



# **LED Driver** Compact dimming

### Diagrams LCAI 35W 350mA-900mA ECO C



100 % load correspond to the max. output power (full load) according to the table on page 2.

#### Additional information

Additional technical information at <u>www.tridonic.com</u>  $\rightarrow$  Technical Data

Guarantee conditions at <u>www.tridonic.com</u>  $\rightarrow$  Services

Life-time declarations are informative and represent no warranty claim. No warranty if device was opened.